

# Modbus : memory addressing to read input datas

FC02 (1x) : 'ReadDiscretInputs' ... to read 'bit'

Modbus_Module	address
function_code : 02	0

ChanDi	number
1	0
2	1
3	2
4	3
5	4

15	14
16	15
17	0
18	1
19	2

First word

table	register	word	Content (16bit)															
			15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
1x	1x0001	1	0	0	0	0	0	0	0	0	0	0	0	0	1	0	1	1
		2	0	1	1	1	0	0	1	0	1	0	0	0	1	0	1	0
		3																
		4																
		x																

Representation : Bit8

Next word